

IT'S A WIRELESS WORLD

AUSTRALIAN DESIGNED AND MANUFACTURED RADIO SYSTEMS



NESS RR3 MICRO RADIO REED SWITCH

- On-board reed switch
- Fully supervised, encrypted signals
- Compatible with all Ness radio receivers
- Lithium battery operation
- Ultra low standby current draw
- Self adhesive pad mount
- Unique Earthing spring for extra range

SPECIFICATIONS

Operating Voltage	3V Lithium battery CR2032
Standby Current Draw	Typically 4 μ A
Signals Transmitted	1. Alarm/Restore 2. Low Battery 3. Supervision signal hourly 4. Learn message
Radio Security	Encryption. Supervised operation.
Frequency	303.85MHz / 868MHz
Indicator	LED (concealed, visible through front housing)
Dimensions	60(h) x 28(w) x 7(d) mm
Weight	20g

SLIMLINE DESIGN



USE WITH ALL NESS PANELS* & RECEIVERS



* Some control panels may require an optional radio interface.



NESS SECURITY PRODUCTS
Australian Communications Authority
RADIO COMMUNICATIONS COMPLIANCE



SYDNEY 02 8825 9222
sales@ness.com.au

MELBOURNE 03 9875 6400
nessmelb@ness.com.au

BRISBANE 07 3399 4910
nessbris@ness.com.au

PERTH 08 9328 2511
nessper@ness.com.au

ADELAIDE 08 8152 0000
adelaide@ness.com.au

NFS (NZ) 09 580 1576
sales@nfs.co.nz



www.ness.com.au