

RLB8 Data Sheet



The 12Vdc powered RLB8 relay board from Tactical Power Products features a strip of eight (8) individual dual buffered, Single Pole / Double Throw (SPDT) Relays which share a common power rail.

Relays may be separated from the strip for individual or group use.

Each relay features a transistor buffered input which may be triggered by any positive DC voltage over 5Vdc or by 0Vdc. (Inputs are provided for + or - trigger)

An onboard LED illuminates when the relay is triggered.

If used in a strip of 8, 12Vdc power need only be connected to one pair of input terminals as all other relays are connected to the power bus.

SPECIFICATIONS:

- Input voltage 12 - 15Vdc
- SPDT relay contacts rated at 6A @ 30Vdc
- Trigger threshold : + 5V to 12Vdc or 0V
- Current draw is 47 mA for each relay when active
- Dimensions: 281L x 47W x 20H mm



RLB8 12Vdc SPDT Relay Board



AUSTRALIA'S PREMIER SECURITY POWER SPECIALIST



Designed & Manufactured
in Australia



OTHER QUALITY PRODUCTS FROM TACTICAL POWER PRODUCTS



TPS24-6DC

24Vdc 6A Power Supply and Charger

TPS13-5DC

13.5Vdc 5A Power Supply and Charger



© 2016 The contents of this manual are copyright and may not be reproduced without permission of - Tactical Power Products Pty Limited.



TIM-01

Universal Digital Timer 1 Sec -99 Days



PDM5

10 Way Power Distribution Board

www.tacpower.com.au or ask your Tactical distributor for details